



- Battery charger and starter for 12/24V WET batteries and rapid cranking of all types of cars, vans, light goods vehicles, excavators, tractors and lorries.
- Fast (BOOST) charge and rapid cranking.
- Remote control. Timer to program timed BOOST charge and avoid overloading the battery.
- Display of charging and cranking current.
- Protection against overcharging and pole inversion.

TECHNICAL DATA

CODE	829008	CHARGE AND STARTING VOLTAGE	12 / 24 V	MIN.RATED REFERENCE CAPAC.	20 Ah
THREEPHASE MAINS VOLTAGE	230 / 400 V	EFFECTIVE CHARGING CURRENT	100 A	MAX.RATED REFERENCE CAPAC.	1600/ 800 Ah
MAINS FREQUENCY	50 / 60 Hz	RATED CHAR.CUR.EN60335-2-29	80 A	ADJUSTMENT POSITIONS	5
CHARGING ABSORBED POWER	2,5 kW	START CUR.1V/C EN60335-2-29	640 A	DIMENSIONS (LxWxH)	38 x 56 x 88,5 cm
STARTING ABSORBED POWER	20 kW	MAX STARTING CURRENT	1000 A	WEIGHT	45 kg

SUPPLIED ACCESSORIES

123467	CABLE 25 MMQ 3 M
123993	REMOTE CONTROL 6 M
123456	CABLE 25 MMQ 2,5 M
712747	POSITIVE CLAMP
712748	WORK CLAMP

OPTIONAL ACCESSORIES

BATTERY CHARGERS FUSES	
802129	FUSES 300A 10 PCS

DESCRIPTION

Battery charger and starter for charging free electrolyte batteries (WET) with 12V/24V voltage and starting all kinds of cars, vans, light trucks, earth moving equipment, tractors and trucks.

Features:

- choice of normal charge, quick charge (BOOST), quick start;
- timer for quick charge;
- remote control;
- display of charging and starting current;
- protection against overloads and polarity reversal.

DOWNLOAD



CATALOG IMAGE



INSTRUCTION MANUAL



SPARE PARTS LIST